

# E36731A Battery Emulator

## Quickly optimize your device for better battery

The E36731A is designed to operate with Keysight BV9211B Pathwave BenchVue advanced battery emulation software. This combination allows you to easily profile batteries and perform battery emulation, enabling you to perform battery drain analysis at different charge levels. This capability allows you to quickly optimize your device for better battery life. You can also create a custom charging and discharging sequence at various test conditions. The software can run one thousand cycle operations to determine the aging effects and the impact on battery reliability.



Keysight E36731A Battery Emulator & BV9211B Software

Model/Option	Description
E36731A	Battery Emulator
BV9211B	PathWave BenchVue Advanced Battery Test and Emulation Software for Single Instrument
BV9210B	PathWave BenchVue Advanced Battery Test and Emulation Software for Four Instrument
EL34GPBU	GPIO user installable interface module
SEC	NISPOM and file security
UK6	Commercial calibration with test result data

E36731A		
DC Power Supply Output Rating		
Power	200W	
Voltage	0 to 30 V	
Current	0 to 20 A	
Programming accuracy $\pm$ (% of output + offset) at $23^{\circ}\text{C} \pm 5^{\circ}\text{C}$ for 12 months.		
Voltage	0.025% + 1.5 mV	
Current	0.035% + 1.5 mA	
Readback accuracy $\pm$ (% of output + offset) at $23^{\circ}\text{C} \pm 5^{\circ}\text{C}$ for 12 months.		
Voltage	0.025% + 1.5 mV	
Current	Low, 0.1 A	0.035% + 10 $\mu\text{A}$
	Mid, 2 A	0.03% + 300 $\mu\text{A}$
	High, 20 A	0.05% + 250 $\mu\text{A}$
Electronic Load Input Rating		
Power	250W	
Voltage	0 to 60 V	
Current	0 to 40 A	
Programming accuracy $\pm$ (% of output + offset) at $23^{\circ}\text{C} \pm 5^{\circ}\text{C}$ for 12 months.		
Constant current mode	Low, 4 A	0.05% + 820 $\mu\text{A}$
	High, 40 A	0.05% + 7.2 mA
Constant voltage mode	Low, 15 V	0.03% + 4.2 mV
	High, 60 V	0.03% + 15 mV
Constant power mode	Low, 0.08 $\Omega$ to 30 $\Omega$	0.1% + 160 mS
	Mid, 10 $\Omega$ to 1.25 k $\Omega$	0.1% + 16 mS
	High, 100 $\Omega$ to 4 k $\Omega$	0.1% + 1.8 mS
Constant power mode	Low, 0.02 W to 5 W	0.08% + 18 mW
	Mid, 0.15 W to 25 W	0.08% + 150 mW
	High, 1.5 W to 250 W	0.08% + 1.5 W
Readback accuracy $\pm$ (% of output + offset) at $23^{\circ}\text{C} \pm 5^{\circ}\text{C}$ for 12 months.		
Current	Low, 4 A	0.05% + 820 $\mu\text{A}$
	High, 40 A	0.05% + 7.2 mA
Voltage	Low, 15 V	0.03% + 4.2 mV
	High, 60 V	0.03% + 15 mV
Power	Low, 0.02 W to 5 W	0.08% + 18 mW
	Mid, 0.15 W to 25 W	0.08% + 150 mW
	High, 1.5 W to 250 W	0.08% + 1.2 W

More Information: [www.keysight.com/find/E36731A](http://www.keysight.com/find/E36731A)

# Key Values

## Battery profiling, emulation, and cycling with BV9211B/BV9210B software

- Power up to 200W, 30V, 20A
- Profile batteries through charge/discharge to create a unique battery model
- Emulate charge states to reduce test time, improve safety, and test repeatability
- Charge/discharge batteries to determine the capacity visually
- Cycle batteries to determine loss of capacity and reduction of battery life

## Two-quadrant operation

### Power supply function

- 200W, 30V, 20A
- Autoranging
- Datalogging
- LIST function
- Voltage slew control

### Electronic load function

- 250W, 60V, 40A
- CC, CV, CR, CP
- Scope function
- Datalogging
- LIST function

## Convenient benchtop capabilities and intuitive interfaces

- Front output terminal, including sense and ground
- 4.3-inch LCD color display
- Individual knobs for voltage and current
- LAN/LXI, USB, and GPIB (requires EL34GPBU upgrade option) interfaces



Learn more at: [www.keysight.com/find/E36731A](http://www.keysight.com/find/E36731A)

## DISTRAME

Parc du Grand Troyes - Quartier Europe Centrale, 40 rue de Vienne - 10300 SAINTE-SAVINE  
Tél. : 03 25 71 25 83 - [infos@distrame.fr](mailto:infos@distrame.fr) - [www.distrame.fr](http://www.distrame.fr)